

**B.TECH**  
**(SEM-III) THEORY EXAMINATION 2019-20**  
**DISCRETE STRUCTURE & GRAPH THEORY**

Time:3 Hours

Total Marks:100

Note: Attempt all Sections. If require any missing data; then choose suitably.

**SECTION – A**

1. Attempt all questions in brief. 2 x 10 = 20

- a) Let A and B be sets. Show that  $AXB \neq BXA$ . Under what condition  $AXB = BXA$ ?
- b) Let R be a binary relation on the set of all positive integers such that:  
 $R = \{(a,b) / a-b \text{ is an odd positive integer}\}$   
 Is R reflexive? Symmetric? Transitive?
- c) Define the Subgroup of a group.
- d) Find the total number of squares in a Chess Board.
- e) Define Lagrange's theorem. What is the use of the theorem?
- f) Define Multiset and Power set. Determine the power set  $A = \{1,2\}$
- g) Define a Partial Ordering.
- h) What is a binary Search tree? Explain with example.
- i) Prove that  $(P \vee Q) \rightarrow (P \wedge Q)$  is logically equivalent to  $P \leftrightarrow Q$ .
- j) Write short note on : Isomorphism of graphs.

**SECTION – B**

2. Attempt any three of the following: 10 x 3 = 30

- a) Let  $f: X \rightarrow Y$  and  $X=Y=R$ , the set of real number. Find  $f^{-1}$  if
  - (i)  $F(x) = x^2$
  - (ii)  $F(x) = (2x-1)/5$
- b) Prove that  $(R, +, *)$  is a ring with zero divisors, where R is  $2 \times 2$  matrix and + and \* are usual addition and multiplication operations.
- c) Describe the Boolean duality principle. Write the dual of each Boolean equations:
  - (i)  $x + x'y = x + y$
  - (ii)  $(x.1)(0+x') = 0$ .
- d) Determine the value of each of there prefix expressions:
  - (i)  $-*2/933$
  - (ii)  $+-*335/\uparrow 232$
- e) Solve the recurrence relation :  
 $a_n = 3a_{n-1} + 4^{n-1}$ , for  $n \geq 0$  &  $a_0 = 1$

**SECTION – C**

3. Attempt any one part of the following: 10 x 1 = 10

- a) Prove that a simple graph with n vertices and k components can have at most  $(n-k)(n-k+1)/2$  edges.
- b) Prove by using mathematical induction that:  
 $7+77+777+\dots+777\dots7 = 7/81[10^{n+1}-9n-10]$  for every  $n \in \mathbb{N}$ .

Paper Id: 

110312
--------

Roll No: 

--	--	--	--	--	--	--	--	--	--	--	--	--	--	--

4. Attempt any one part of the following: 10 x 1 = 10

- a) Define preorder, inorder and postorder tree traversal. Give an example of preorder, postorder & inorder traversal of a binary tree of your choice with at least 12 vertices.
- b) Let R be a relation on R, the set of real numbers, such that  $R = \{(x, y) \mid |x - y| < 1\}$ . Is R an equivalence relation? justify.

5. Attempt any one part of the following: 10 x 1 = 10

- a) Draw the Haase diagram of  $[p(a, b, c), \leq]$ , Find greatest element, least element, minimal element & maximal element.
- b) Simplify the following Boolean function using three variables maps:
  - (a)  $f(x, y, z) = \sum(0, 1, 5, 7)$
  - (b)  $f(x, y, z) = \sum(1, 2, 3, 6, 7)$

6. Attempt any one part of the following: 10 x 1 = 10

- a) Express this statement using quantifiers:  
“Every student in this class has taken some course in every department in the school of mathematical sciences”.
- b) Solve the recurrence relation by the method of generating function.  
 $a_r - 7a_{r-1} + 10a_{r-2} = 0, r \geq 2$ , Given  $a_0 = 3$  and  $a_1 = 3$ .

7. Attempt any one part of the following: 10 x 1 = 10

- a) Let  $(A, *)$  be a monoid such that for every  $x$  in  $A$ ,  $x * x = e$ , where  $e$  is the identity element. Show that  $(A, *)$  is an abelian group.
- b) Constructed the truth table for the following statements:
  - (i)  $(P \rightarrow Q') \rightarrow P'$
  - (ii)  $P \leftrightarrow (P' \vee Q')$