



Printed Pages : 3

<http://www.uptuonline.com>

TCS301

(Following Paper ID and Roll No. to be filled in your Answer Book)

**PAPER ID : 1064**

Roll No.

--	--	--	--	--	--	--	--	--	--

**B.Tech**

**(SEM III) ODD SEMESTER THEORY EXAMINATION 2009-10**  
**DISCRETE STRUCTURE**

*Time : 3 Hours]**[Total Marks : 100***Note :** *Attempt all questions.***1** Attempt any **four** parts of the following : **5×4=20**

(a) Show that  $(R \subseteq S) \wedge (S \subset Q) \Rightarrow R \subset Q$ . Is it correct to replace  $R \subset Q$  by  $R \subseteq Q$ .. Explain your answer.

(b) Let  $N = \{0, 1, 2, 3, \dots\}$ . Define functions  $f, g$  and  $h$  from set  $N$  to  $N$  by  $f(n) = n+1$ ,

$$g(n) = 2n, h(n) = \begin{cases} 0 & \text{if } n \text{ is even} \\ 1 & \text{if } n \text{ is odd} \end{cases}$$

Compute  $go(fog)oh$ .

Is the function  $h$  is invertible ?

Is the function  $f$  is on to ?

(c) Given a covering of the set  $S = \{A_1, A_2, \dots, A_n\}$ , show how you can write a compatibility relation which defines this covering.

**JJ-1064]****1****[Contd...**

- (d) Let  $f: X \rightarrow Y$  and  $g: Y \rightarrow X$ . Prove that the function  $g$  is equal to  $f^{-1}$  only if  $g \circ f = I_X$  and  $f \circ g = I_Y$ .
- (e) Show that the predicate "x is prime" is primitive recursive.
- (f) Show that  $n^3 + 2n$  is divisible by 3.
- 2 Attempt any **four** parts of the following : 5×4
- (a) If  $G$  is a group in which  $(ab)^i = a^i b^i$  for three consecutive integers  $i$  and any  $a, b$  in  $G$ , show that  $G$  is abelian.
- (b) Show that the intersection of any two congruence relations on a set is also a congruence relation.
- (c) Show that the relation of isomorphism is an equivalence relation.
- (d) Show that every finite semigroup has an idempotent.
- (e) Show that for any commutative monoid  $\langle M, * \rangle$ , the set of idempotent elements of  $M$  forms a submonoid.
- (f) Write about cosets and permutation groups.
- 3 Attempt any **two** parts of the following : 10×2=20
- (a) Give an example of a set  $X$  such that  $\langle \rho(X), \subseteq \rangle$  is a totally ordered set.
- (b) Prove that a  $n$  variable boolean function having products of all maxterm is zero.
- (c) (i) Define Binary search tree. Show the insertion of an element in an existing binary search tree.
- (ii) Prove that a tree with  $n$  vertices will have  $n-1$  edges.



- 4 Attempt any **two** of the following parts : 10×2  
<http://www.uptuonline.com>
- (a) (i) Write the following statement in symbolic form. "If either Ram takes Maths or Shyam takes Science, then Hari will take Biology".
- (ii) Construct the truth table for  
 $(P \rightarrow Q) \wedge (Q \rightarrow P)$ .
- (b) Obtain formulas having the simplest possible form which are equivalent to formulas :
- (i)  $P \vee (\neg P \vee (Q \wedge \neg Q))$ .
- (ii)  $(P \wedge (Q \wedge S)) \vee (\neg P \wedge (Q \wedge S))$ .
- (c) Show that  $\neg P(a, b)$  follows logically from (x)  
 (y)  $(P(x, y) \rightarrow w(x, y))$  and  $\neg W(a, b)$ .

- 5 Attempt any **two** of the following parts : 10×2
- (a) (i) Solve the recurrence relation  $dn = 2 dn - 1 - dn - 2$ .
- (ii) Write about linked list representation of graphs.
- (b) Show that if  $G$  be a graph of  $n$  vertices and  $m$  edges then  $G$  has Hamiltonian circuit if  

$$m \geq \frac{1}{2} (n^2 - 3n + 6)$$
.
- (c) (i) Prove that a tree of connected graph has no circuit.
- (ii) Define Euler graph. Give a suitable example for it.